

DATA SHEET

Triac Common Dimmer

- The product uses a single wire technology, connecting with lamps in series.
- The product enable to control the light level by press of button in 16 preset profiles.
- Usually, household lamps and lanterns uses 2 wire system, however the product adopts single wire transmission.
- Dimmer include over temperature protection that automatically cut off power when the temperature is above 95°C. when product temperature is below 50°C. It will return to normal operation.

Working temperature: -20-95°C

Voltage supply: 220V 50Hz

External dimension: L47*W33*H20 mm

Output: 1channel

Max output current: 2.5A

Net weight: 55.Og

Fuse size: 250V-5A-95°C

Max output power: 500W Resistive load
100W Led load

Tools for installation: Phillips screwdriver and slot

Compatible Countries: Universal.



2.5A

220
VAC

50Hz

95°C



PRODUCTS:

כמות בקרטון	משקל יחידה	צבע	תאור פריט	דגם	מספר קטלוגי
10	30 גרם	שחור	דימר אוניברסלי נסתר	DM017	DDM05000001

DRAWINGS: (mm)

